

# SERIES 810

## High/Low Bay

### NARROW



OPTIONS

6-LAMP VERSION



WIRE GUARD CLIPS



WIRE GUARD



OPTIONS

### Application

- Low bay/high bay warehouses/manufacturing facilities
- Sport facilities and multifunction rooms
- Big box stores and retail facilities

### Finishes Available

Frame:

- Standard in white CRS

Reflectors:

- Aluminum enhanced 95% reflectance
- White steel 86% reflectance

### Features

- Ceiling mounted or suspended with cables, stems or chains by others
- Reflectors available with 5% up-light or 100% down-light
- Two computer designed individual reflectors install with quarter-turn fasteners (provided)
- Frame accommodates 4 or 6 T5HO lamps; 4 or 6 T8 lamps or a combination of T5HO and T8 lamps
- Space available for 4 ballasts, motion sensors and remote control switching.
- Only 2 1/2"H X 15 9/32"W X 50 5/32"L and weighs 13 pounds without ballasts.

### Optional Features

- Optional stylized frame available that will accommodate louvers and lenses for low bay application. Hinged torsion springs for re-lamping. Contact factory for availability.
- Optional 11-gauge wire guard with clips for hanging. Can be used with the stylized frame.
- Luminaire can be differentiated to accommodate your design objectives

Custom modifications in the physical specification and color are available for this fixture.

### Lamping Options

T5HO	T8
(4) 54W	(4) 32W
(6) 54W	(6) 32W

### Packaging

Bodies	2
Reflectors	36



PATENT APPLIED FOR



# SERIES 810

## HIGH/LOW BAY

## NARROW



### Lamping Options

T5HO	T8
(4) 54W	(4) 32W
(6) 54W	(6) 32W

REV 10-25-05





## ASSEMBLY INSTRUCTIONS

1. Mount ballast to the ballast bracket.
2. Mount ballast bracket(s) to frame with (B) and (C).
3. Insert snap bushings (D).
4. Feed wires through for sockets and power.
5. Insert center cover over center support on frame with (A).
6. Insert side frames covers to frame assembly with (A).
7. Insert end covers to frame assembly with hardware (A).
8. Flip assembly and mount reflectors with (E).

NOTE: Peel protective coating off of reflector before hanging the fixture.

NOTE: When using T-8 lamps use grommets to plug off T-5 socket hole.

Grommets can be purchased at Gaynor Corp. (203) 378-5545 (Part #: WG-2)

## INSTALLATION INSTRUCTIONS

1. Take reflectors out of assembly.
2. Mount and wire assembly. You can use multiple options: Chain, Flush, Cable, etc.
3. After assembly is mounted safely you can install reflectors and lamp fixture.

## RECOMMENDED SOCKETS

### T8/G13

Stucchi: 1345/FAU-9.5

Vossloh: 101749

BJB: 26.422.1009.50

ALP: LH300-28

Etlin Daniels: FL421

### T5/G5

Stucchi: 268

Vossloh: 108660

BJB: 26.620.2204.50

ALP: LH150-11

Etlin Daniels: FL622-L

## HARDWARE LIST (by others)

(A) 8-32 Sheetmetal Screw 1/4" long (13 pcs.)

(B) 8-32 Machine Screw 1/4" long (4 pcs.)

(C) 8-32 Flat Washer (4 pcs.)

(D) Snap Bushing (6 Pcs.) / Heyco Part# 2813

(E) 1/4 Turn Fastener (4 pcs.) / Supplied

